



- Off-time measurement for Protecting Residual-Differential Current devices according to the specified default current selectable from 3 mA to 0.5 A.
- Microprocessor Controlled.
- Liquid Crystal Display (LCD) 2 lines x 16 characters.
- Very Low Consumption.
- Zero crossing detection, allows to verify in the two half-waves.
- Accurate Digital Readout of Disconnection Time.
- Measure Voltage Between Line and Earth Before Testing.
- Wiring Polarity Indicator.

DIGITAL RCD TESTER

Test current	3, 5, 10, 15, 20, 30, 50, 100, 150, 250, 300, 500 mA.
Current Selection	Rotary Switch Selector.
Phase Start Selection	0° and 180° Referenced to Earth.
Phase Polarity Trip Indication	Graphical indication on LCD display. Referenced to Earth.
Operating Voltage (L-E) 50 Hz or 60 Hz	230 V AC.
Voltmeter (L-E)	20 V AC ~ 280 V AC.
Maximum input voltage	280 V AC.
Timer Resolution	1 ms (Max Time = 2.999 s).
Timer Accuracy	± (2 % rdg + 1 dgt).
Voltmeter Resolution	1 V AC.
Voltmeter Accuracy	1 V AC ± 2%.
Power supply	
Batteries	9 V DC (6 batteries x 1.5V R6 type).
Operating environmental conditions	
Altitude	Up to 2000 m.
Rel. temp. and humidity	From -5 to 45 °C and 85% from H. R.
Storage temperature	From -10 to 45 °C.
Included accessories	PP011 Set of three safety clamps-banana cables. User's manual. Transport suitcase.