

SUPA8 Programming Quick Reference Software Version 20

	Default 1	Default 2	Domestic	Business
	Local	Personal Dialling	Monitored	Monitored
Panel Options 1	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8
Address 096	<input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y	<input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y	<input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y	<input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y
Available options>>	1=Display lights 2=Quick away 3=Quick home 4=Code 15 once 5=AC Fail delay 6=Quick review 7=Power codes			

Panel Options 2	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8
Address 098	<input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y	<input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y	<input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y	<input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y <input type="checkbox"/> Y
Available options>>	1=Exit beep 2=Entry beep 3=Exit squawk 4=Entry squawk 5=Home squawk 6=On/Off squawk 7=Home instant 8=No arm low batt.			

General Options	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8
Address 240	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
Available options>>	1=Enable external zones 2 & 3=one input sensitivity 4=Squawk or flash 6=Zone 8 home key 7=Zone 7 siren toggle			

Dialler Options	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8
Address 170	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> Y <input type="checkbox"/> Y	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> Y <input type="checkbox"/> Y
Available options>>	1=Rotary dialling 2=Send opening after alarm 6=Send zone ID in personal dialling 7=Send restoral reports 8=Send isolated zone reports			

Dialler Format	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8	1 2 3 4 5 6 7 8
Address 174	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> Y <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> Y <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>	<input type="checkbox"/> <input type="checkbox"/> Y <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/> <input type="checkbox"/>
Available options>>	1=High speed 3=Contact ID 4=Personal dialling			

Maximum dial attempts	Address 175	<input type="text" value="0"/>	<input type="text" value="2"/>	<input type="text" value="6"/>	<input type="text" value="6"/>
Available options>>		0 - 99 attempts			

Attempts before fail to communicate	Address 242	<input type="text" value="0"/>	<input type="text" value="0"/>	<input type="text" value="5"/>	<input type="text" value="5"/>
Available options>>		0 - 99 attempts			

Address 240, options 2 & 3

<u>Input sensitivity</u>	<u>Light 2</u>	<u>Light 3</u>
Normal (default)	OFF	OFF
High	ON	OFF
Medium	OFF	ON
Low	ON	ON

Contact ID Reporting Codes

These values apply where Contact ID reporting format is selected.

	Address	Value
On / Off input	176	401
Fail to communicate	179	000
spare	182	000
Zone 1	185	130
Zone 2	188	130
Zone 3	191	130
Zone 4	194	130
Zone 5	197	130
Zone 6	200	130
Zone 7	203	110
Zone 8	206	137
Duress input	209	121
Panic input	212	120
Test input	215	601
Low battery	218	302
AC Fail	221	301

Other Options

These values apply to all defaults

	Address	Value
Required rings to answer phone	168	15
Zone pulse count (if enabled)	243	3
Zone pulse time	244	90
Default 1. Local	250	1578
Default 2. Personal	250	2578
Default 3. Domestic monitored	250	3578
Default 4. Business monitored	250	4578
Panel reset	254	